

# SmartSight S1712e

## 12-Input Ethernet Video Server



SmartSight  
1712e is a cost-effective  
multi-port video solution.



SmartSight® S1712e Ethernet video server is a cost-effective, multi-port solution designed for video monitoring and surveillance applications in which a high concentration of cameras terminates within the same area.

The S1712e delivers MPEG-4-based video over 10/100Base-T networks using cat 5, fiber optic, and wireless media.

Compactly designed, the S1712e accommodates 12 video inputs within a 1U, 6-inch (15-cm) depth enclosure. Multiple units can be rack mounted on one or both sides of a standard 19-inch (48-cm) cabinet.

The S1712e is available in three configurations: S1712e-T with 12 analog video inputs, S1712e-T-A with 12 analog video inputs and bidirectional audio, and S1712e-T-12iA with 12 analog video inputs and 12 audio inputs.

Configuration and management are made easy with the ndVR™, Loronix Video Manager®, or SConfigurator software.

- ✓ Compact footprint: 12 input video streams in 1U enclosure
- ✓ MPEG-4-based video input
- ✓ Scalable resolution from 352 x 240 to 704 x 480 NTSC pixels (352 x 288 to 704 x 576 PAL pixels)
- ✓ SSL-based user authentication
- ✓ RS-422/485 serial port to support motorized domes and cameras
- ✓ 12 discrete alarm inputs and two relay outputs
- ✓ Optional bidirectional audio interface for microphone or line-level input, and headphone or line-level output
- ✓ Optional 12 input audio interface for up to 12 microphones or line-level inputs

| NETWORK                         |   | PHYSICAL  |  |
|---------------------------------|---|---|--|
| Interface                       | Ethernet 10/100Base-T   | Enclosure   | Metal case with flange mount (black color)   |
| Connector                       | RJ-45 jack  | Size  | 17L x 6.1W x 1.7H in. (431.8L x 154.9W x 43.2H mm)   |
| Protocols                       | Transport: RTP/IP, UDP/IP, TCP/IP, or multicast IP<br>Others: DNS and DHCP client   | Weight  | 5.6 lb (2.6 kg)  |
| Security                        | SSL-based authentication  | Environmental                                     | 32°F to 122°F (0°C to 50°C)  |
| VIDEO                           |   | Humidity  | 95% non condensing at 122°F (50°C)   |
| Input                           | 12 composites, 1 Vpp into 75 ohms (NTSC/PAL)  | MANAGEMENT  |  |
| Connectors                      | BNC female connectors   | Configuration *                                   | Remote: via nDVR, Loronix Video Manager, SConfigurator, or Telnet<br>Local: via the serial port using any ASCII terminal |
| Termination                     | 75-ohm video termination per input  | Firmware upgrade                                  | Flash memory for upgrade of video codec and application firmware over the network  |
| Compression                     | MPEG-4-based  | CERTIFICATION AND REGULATION                      |  |
| Resolution                      | Scalable from 352 x 240 to 704 x 480 NTSC pixels (352 x 288 to 704 x 576 PAL pixels)  | Canada  | ICES-003/NMB-003 class A   |
| Frame rate                      | 12 at 1-30 fps in NTSC (1-25 fps in PAL) programmable (full motion)   | USA   | FCC part 15 (subpart B, class A)   |
| Bandwidth                       | Each stream is configurable between 30 kbps and 4 Mbps  | Europe  | CE marked, EN 55022:1998 class A, EN 55024   |
| SERIAL PORT                     |   | WARRANTY  |  |
| Electrical levels               | Port 1: RS-232 (max. 230 kbps)<br>Port 2: RS-422/485 2/4 wires (max. 230 kbps)  | 3-year limited warranty, covering parts and labor |  |
| Connectors                      | Port 1: DB-9<br>Port 2: pluggable screw-terminal strip  | ORDERING  |  |
| Operating mode                  | Transparent serial port supporting any asynchronous serial protocol   | Part number                                       | S1712e-T   |
| ALARM AND AUDIO                 |   | Description                                       | 12-input Ethernet video server encoder   |
| Alarm                           | Input: 12 dry contacts<br>Output: 2 relay contacts (48V AC/DC at 100 mA max.)   | Part number                                       | S1712e-T-A   |
| Bidirectional audio (optional)  | Input: -46 to -3 dBV into 1 kOhm<br>Output: -46 to -3 dBV into 16 ohms min.<br>Connectors: One set of 0.14 in. (3.5 mm) input and output stereo jacks                         | Description                                       | 12-input Ethernet video server encoder with single audio port  |
| Unidirectional audio (optional) | Input: -46 to -3 dBV into 30 kOhm<br>Programmable bias: 0-9V DC<br>16-bit resolution<br>8, 16, or 24 KHz sampling rate<br>Connectors: 12 0.14 in. (3.5 mm) input stereo jacks | Part number                                       | S1712e-T-12IA  |
| POWER                           |   | Description                                       | 12-input Ethernet video server encoder with 12 audio inputs  |
| Supply voltage                  | 12V DC +/- 10%  | OPTIONAL ACCESSORIES                              |  |
| Consumption                     | 24W (2A at 12V DC) max.   | Part number                                       | PDP10  |
|                                 |   | Description                                       | 19-inch (48-cm) power distribution panel rack mount. Supports up to ten S1712e encoders                                  |
|                                 |   | Part number                                       | PS1260   |
|                                 |   | Description                                       | 110V AC to 12V DC power supply for a single unit   |
|                                 |   | Part number                                       | PS1280   |
|                                 |   | Description                                       | High capacity power supply for rack mount installations (to be used with PDP10)  |

\* Product capabilities are enabled through software.

AIRLINX Communications, Inc.  
Box 253  
Greenville, NH 03048  
E-mail: sales@airlinx.com  
Tel: (888) 224-6814  
Fax: (603) 878-0530